

Runs for up to 12 hours on its built-in rechargeable battery.

40 watts of power; enough to drive an additional pair of unpowered speakers for even greater coverage.




Diagram of Porta-Vox control panel.

## MODELS

PB-500 Battery-powered 40-watt system; includes mic and charger.

## WIRELESS

PB-500W Porta-Vox with built-in wireless receiver. (order mic separately). WH-58

Handheld wireless microphone/ transmitter.

CM-60/WB-II CollarMic microphone with wireless body-pack transmitter.

HBM-60/WB-II Headband microphone with wireless body-pack transmitter.

## ACCESSORIES

SS-250 Speaker stand. SP-500 Unpowered companion speaker pack (2 speakers with cables). VL-500 Storage cover. CC-450 Speaker stand bag. SC-50EX 50' speaker cable extension. MIC-90P Handheld microphone; balanced, low impedance.

## SPECIFICATIONS

PB-500, PB-500W Rated power output: Max SPL @ rated power: Frequency response: Mic input 1: Mic input 2:

Line input Battery type: Operation time: Charger (Anchor RC-16): Dimensions: Weight: 2 x 20 watts @  $3\Omega$ 123 dB @ 1 meter 250 Hz - 10 kHz  $\pm$  4 dB Lo-Z, unbalanced, 1/4"-phone Lo-Z, unbalanced, 1/4"-phone (used for wireless on PB-500W) Hi-Z, unbalanced, 1/4"-phone 12 volt rechargeable, 7.0 AH 10-12 hours (dependent upon use) 16 volts AC, 1.5A, 60Hz 27 x 9.5 x 14", 69 x 24 x 35 cm 30 pounds, 13.5 Kg. Specifications subject to change without notice.

